



DESCRIPTION / APPLICATION

CJX2 AC contactor D series (hereinafter referred to as contactor) is mainly used circuits of AC50/60Hz, voltage up to 660V, and current up to 95A, for long-distance switching on/off the circuits and frequent start-up and control of AC motor, and it can be combined with appropriate thermal relay to constitute electromagnetic starter, in order to protect circuits that may subject to operating overload. It is in conformity with IEC 60947-4 standard.

MAIN TECHNICAL DATA

| Type | CJX2-D09 | CJX2-D12 | CJX2-D18 | CJX2-D25 | CJX2-D32 | CJX2-D40 | CJX2-D50 | CJX2-D65 | CJX2-D80 | CJX2-D95 |
|---------------------------------------|---|----------|----------|----------|----------|--|----------|----------|----------|----------|
| Rated Insulation Voltage | 660 | 660 | 660 | 660 | 660 | 660 | 660 | 660 | 660 | 660 |
| Conventional Thermal Current | 20 | 25 | 32 | 40 | 50 | 60 | 75 | 80 | 110 | 125 |
| Rated Operational Current 380V/AC3 | 9 | 12 | 18 | 25 | 32 | 40 | 50 | 63 | 80 | 95 |
| Power of Controlled (kW) | 2.2 | 3 | 4 | 5.5 | | 11 | 15 | 18.5 | 22 | 25 |
| | 4 | 5.5 | 7.5 | 11 | | 18.5 | 22 | 30 | 37 | 45 |
| | 4 | 5.5 | 9 | 11 | | 22 | 25 | 37 | 45 | 45 |
| | 4 | 5.5 | 9 | 11 | | 22 | 30 | 37 | 45 | 45 |
| | 5.5 | 7.5 | 10 | 15 | | 30 | 33 | 37 | 45 | 45 |
| Installation | 1. Two screw mounted 2. Din mounted (35mm) | | | | | 1. Three screw mounted 2. Din mounted (35mm / 75mm) | | | | |

DIMENSIONS(MM)

| | 9A | 18A | 25A | 32A | 65A | 80A, 95A |
|---------------|----|------|------|------|-------|----------|
| Length | 72 | 72 | 81.5 | 81.5 | 106.5 | 121.5 |
| Width | 46 | 46 | 57 | 57 | 74.5 | 85 |
| Height | 80 | 85.5 | 100 | 93.7 | 114 | 123 |

